

#	From Router/Tx - To Router/Tx	#	From Router/Tx - To Router/Tx	#	From Router/Tx - To Router/Tx	#	From Router/Tx - To Router/Tx
1	A/T0 - B/T0	7	C/T2 - B/T2 + D/T2	13		19	
2	B/T1 - A/T0	8	D/T2 - A/T1	14		20	
3	B/T1 - C/T0 + D/T0	9	D/T2 - E/T1	15		21	
4	C/T1 - E/T0	10		16		22	
5	E/T1 - D/T1	11		17		23	
6	D/T2 - B/T1 + C/T1	12		18		24	

FROM FINAL
SP 16 VERSION 1
QUESTION 2

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 0	10.0.0.0	0	Dir							10.0.0.0	0	Dir			
	20.0.0.0	0	Dir	20.0.0.0	0	Dir									
				30.0.0.0	0	Dir	30.0.0.0	0	Dir	30.0.0.0	0	Dir			
							40.0.0.0	0	Dir				40.0.0.0	0	Dir
										50.0.0.0	0	Dir	50.0.0.0	0	Dir

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 1	10.0.0.0	0	Dir	10.0.0.0	1	20.0.0.1	10.0.0.0	2	30.0.0.2	10.0.0.0	0	Dir	10.0.0.0	3	40.0.0.3
	20.0.0.0	0	Dir	20.0.0.0	0	Dir	20.0.0.0	1	30.0.0.2	20.0.0.0	1	30.0.0.2	20.0.0.0	2	40.0.0.3
	30.0.0.0	1	20.0.0.2	30.0.0.0	0	Dir	30.0.0.0	0	Dir	30.0.0.0	0	Dir	30.0.0.0	1	40.0.0.3
							40.0.0.0	0	Dir				40.0.0.0	0	Dir
										50.0.0.0	0	Dir	50.0.0.0	0	Dir

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 2	10.0.0.0	0	Dir	10.0.0.0	1	20.0.0.1	10.0.0.0	1	30.0.0.4	10.0.0.0	0	Dir	10.0.0.0	1	50.0.0.4
	20.0.0.0	0	Dir	20.0.0.0	0	Dir	20.0.0.0	1	30.0.0.2	20.0.0.0	1	30.0.0.2	20.0.0.0	2	40.0.0.3
	30.0.0.0	1	20.0.0.2	30.0.0.0	0	Dir	30.0.0.0	0	Dir	30.0.0.0	0	Dir	30.0.0.0	1	40.0.0.3
	40.0.0.0	2	10.0.0.4	40.0.0.0	2	30.0.0.4	40.0.0.0	0	Dir	40.0.0.0	1	50.0.0.5	40.0.0.0	0	Dir
	50.0.0.0	1	10.0.0.4	50.0.0.0	2	30.0.0.4	50.0.0.0	1	30.0.0.4	50.0.0.0	0	Dir	50.0.0.0	0	Dir

CMP-405

Final Exam

Name: _____

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 3				10.0.0.0	1	20.0.0.1									
				20.0.0.0	0	Dir									
				30.0.0.0	0	Dir									
				40.0.0.0	1	30.0.0.3									
				50.0.0.0	1	30.0.0.4									

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 4															

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 5															

	A			B			C			D			E		
	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route	Network	Hops	Route
T 6															